

## ■ LED Lamp

### [Features and Benefits]

Rated input voltage 100-242V

One Side power supply / Built-in power supply

Made of glass

Usually, Wire work on the lighting equipment is required(QR code),  
glow-starter type light fixtures can use without wiring work.

(※1)With using a dummy-glow,this lamp can be used for using FG-1P or FG-4P glow-stater type fixtures,  
however this lamp is recommended to be used with re-wiring work for reason as below.

(※2)When using a dummy-glow,performance of this lamp depends on condition of a ballast,sockets or other factors.



	Model No.	Color temperature	Base	External size (mm)		Net weight (g)	Lamp voltage (V)	Luminous flux (lm)	Power consumption (W)	Normal lamp-lifetime (h)
				Overall length (L)	Diameter (D)					
Equivalent of 20W fluorescent lamps	ST8A-0.6M 8.7W/865	Cool Daylight (6500K)	G13	580	28	100	100-242	1,050	8.7	50,000
	ST8A-0.6M 8.7W/850	Daylight (5000K)	G13	580	28	100	100-242	1,050	8.7	50,000
	ST8A-0.6M 8.7W/840	Cool White (4000K)	G13	580	28	100	100-242	1,050	8.7	50,000
Equivalent of 40W fluorescent lamps	ST8A-1.2M 17.5W/865	Cool Daylight (6500K)	G13	1,198	28	190	100-242	2,100	17.5	50,000
	ST8A-1.2M 17.5W/850	Daylight (5000K)	G13	1,198	28	190	100-242	2,100	17.5	50,000
	ST8A-1.2M 17.5W/840	Cool White (4000K)	G13	1,198	28	190	100-242	2,100	17.5	50,000

- ※Specification might be changed without notices.
- ※Do not use with dimmer, even for full power.
- ※Never modify this lamp.
- ※Never use for DC power supply.
- ※Never use for emergency light fixtures and guide light fixtures.
- ※Rated life is average value,not for guarantee.



Please check here "Bypass wiring for LED conventional fluorescent lamp wiring".

### [Information]

## OSRAM LEDVANCE

General Agency  
KOYO Denki.co.ltd  
3-1-18 Hiyoshi-town, Nagata-ward,  
Kobe city, Hyogo preecture  
653-0039

TEL:078-631-1212 FAX:078-647-5511  
<http://www.koyodenki.co.jp>  
E-mail:ship@koyodenki.co.jp

### Sales Agency